

简体中文 便携高清无损音乐播放器

机器接口介绍

① 音量旋钮	⑥ 指示灯	⑪ 3.5mm耳机/线路同轴输出口
② 电源/锁屏键	⑦ HOLD开关	⑫ 2.5mm平衡耳机输出口
③ 上一曲键	⑧ 音量加键	⑬ 4.4mm平衡耳机/线路输出口
④ 播放/暂停键	⑨ 音量减键	⑭ Type-C数据/充电端口
⑤ 下一曲键	⑩ 多功能键	⑮ TF卡槽

注:图片仅供参考,具体以实物为准

开/关机

长按电源/锁屏键开机,首次开机时,选择相应语言,点击完成进入主界面;开机状态下长按电源/锁屏键出现关机提示框,可选择关机或重启。

充电

M155支持快充,为达到设计的充电时间,推荐选用符合QC3.0或支持PD协议的USB充电器。

1

简体中文 便携高清无损音乐播放器

手势操作

返回上一级:从屏幕左边缘向右滑动,或屏幕右边缘向左滑动
返回桌面:从屏幕下方上滑
多任务管理:从屏幕下方上滑并停留

工作模式切换

M155拥有5种工作模式,分别为安卓模式、纯音模式、USB DAC模式、蓝牙接收模式、AirPlay模式,首次开机将默认为安卓模式,您可以在下拉菜单,或设置菜单中点击工作模式来切换到其他工作模式。

安卓模式/纯音模式:

使用电脑连接M155传输数据前,您需要安装MTP驱动,请前往官网下载对应系统的驱动,并按相应教程安装驱动后使用;
USB解码模式:
首次切换到USB解码模式时,您需要前往官网下载USB DAC驱动,并按照相应教程安装驱动后方可使用USB解码功能;
蓝牙接收模式:
首次切换到蓝牙接收模式时,M155将自动进入配对状态,后续再次进入蓝牙接收模式时将自动回连上一次连接设备。
强制进入配对模式:长按播放/暂停键约3秒
手动回连:在未连接状态下短按播放键
清除配对:同时长按上一曲键和下一曲键约3秒
播放/暂停:短按播放/暂停键
上一曲/下一曲:短按上一曲键/下一曲键

AirPlay模式:

AirPlay模式工作时需要接入WiFi网络,进入AirPlay前请确认M155已连接正常可用的网络。

注:MAC系统的MTP驱动、以及Windows系统的USB DAC驱动可查看本机FiO Driver磁盘,或者通过下载地址:http://www.fio.com/Driver_Download进行下载;

HOLD开关功能

HOLD开关启用后,M155侧面按键将会被锁定无法操作,防止误触。您可以在设置菜单中选择需要锁定操作的按键,或者通过取消HOLD开关来恢复按键功能。

超级大耳模式

当检测到快充适配器插入时,增益设置会新增“超级大耳模式”菜单,同时系统会弹窗提示“是否需要切换为超级大耳模式”,请根据需要选择是否切换。

2

简体中文 便携高清无损音乐播放器

固件升级

OTA在线升级

打开WiFi并连接到可用网络即可自动检测是否有新版本固件更新。若未检测到新版本,可尝试前往“技术支持-固件升级-在线升级”,点击“检查更新”进行手动检测更新。

TF卡升级

请前往官网下载升级固件,并按相应教程进行版本升级。
下载地址:http://www.fio.com/supports

注意事项

- ★不可自行维修、拆卸和将产品放在有水的地方;
- ★当长期没有使用本产品时,需要定期给产品充电,以保证电池寿命;
- ★请勿将电池置于高温环境中,电池浸水后禁止使用,若电池出现严重膨胀,请勿继续使用,禁止拆解、撞击、挤压电池或将电池投入火中;
- ★搭配电压过高的充电适配器充电可能会损坏机器,请选择推荐使用的充电器进行充电;
- ★系统发生故障导致死机时,可尝试长按“电源/锁屏键”10秒以上,强制重启机器。

包装清单

(请核对包装内是否包括以下物品)

- M155主机
- 皮套
- USB数据线
- 快速入门
- 售后维修卡
- 卡针

了解更多

- 了解产品更多信息请访问FiO官网介绍:
http://www.fio.com
- 了解产品详细使用说明请访问
http://www.fio.com/supports下载相关文件查阅。
- 在M155的“设置-系统-法律信息”中,可查看产品的CMIIT-ID

3

简体中文 便携高清无损音乐播放器

产品名称:便携高清无损音乐播放器
产品型号:M155
额定输入:5V=2A
尺寸:约140x80x18.9mm
重量:约345g
执行标准:Q/FADZ 1-2017
制造厂:广州飞傲电子科技有限公司
地址:广州市白云区龙归街夏良龙良路21号

由于产品不断改进,各项规格及设计随时更改,恕不另行通知。

微功率短距离设备声明

•本产品符合“微功率短距离无线电发射设备目录和技术要求”中通用微功率设备的技术要求,用于数据传输应用;采用一体化天线,控制,调整及开关等使用方法请参考产品说明书中相关内容。
•不得擅自改变使用场景或使用条件、扩大发射频率范围、加大发射功率(包括额外加装射频功率放大器),不得擅自更改发射天线;
•不得对其他合法的无线电台(站)产生有害干扰,也不得提出免受有害干扰保护;
•应当承受射频频率能量的工业、科学及医疗(ISM)应用设备的干扰或其他合法的无线电台(站)干扰;
•如对其他合法的无线电台(站)产生有害干扰时,应立即停止使用,并采取消除措施消除干扰后方可继续使用;
•在航空器内和依据法律法规、国家有关规定、标准划设的射电天文台、气象雷达站、卫星地球站(含测控、测距、接收、导航站)等军民用无线电台(站)、机场等的电磁环境保护区域内使用微功率设备,应当遵守电磁环境保护及相关行业主管部门的规定;
•禁止在以机场跑道中心点为圆心、半径5000米的区域内使用各类模型遥控器;
•微功率设备使用温度为-10℃~+55℃,适用于电池供电为3.8V,使用Type-C供电为5V。

4

环保材料说明

产品中有害物质的名称及含量

部件名称	有害物质					
	铅 (Pb)	汞 (Hg)	镉 (Cd)	六价铬 (Cr,VI)	多溴联苯 (PBB)	多溴二苯醚 (PBDE)
PCB	X	O	O	O	O	O
PCBA 焊点	X	O	O	O	O	O
元器件	X	O	O	O	O	O
显示屏*	X	O	O	O	O	O
电池*	X	O	O	O	O	O
外观件	O	O	O	O	O	O
配件*	X	O	O	O	O	O

注:表中标记“X”的部件,皆因全球技术发展水平限制而无法实现有害物质的替代。带“*”号部件表示如果在您所购买的产品中无该部件,请忽略表中该部件信息。
O:表示该有害物质在该部件所有均质材料中的含量均在GB/T 26572-2011规定的限量要求以下。
X:表示该有害物质至少在该部件的某一均质材料中的含量超出GB/T 26572-2011规定的限量要求。

根据中国电子行业标准SJ/T 11364-2014和相关的中国法律法规,本产品及其某些内部或外部组件上可能带有环保使用期限标识,取决于组件和组件制造商,产品及其组件上的使用期限标识可能有所不同。组件上的使用期限标识优先于产品上任何与之相冲突的或不同的环保使用期限标识。

此环保使用期限只适用于产品在规定的条件下工作

5

English Portable High Resolution Music Player

Buttons and Ports Labeled

① Volume knob	⑥ Indicator light	⑪ 3.5mm headphone out/line out/coaxial output
② Power/Lock button	⑦ HOLD switch	⑫ 2.5mm balanced headphone out
③ Previous track	⑧ Volume up	⑬ 4.4mm balanced headphone out/line out
④ Play/Pause	⑨ Volume down	⑭ Type-C data/Charging port
⑤ Next track	⑩ Multifunction button	⑮ MicroSD card slot

Note: Pictures are for reference only. The actual product may vary.

Power on/off

Hold the Power/Lock button to turn on the M155. On its first startup, tap the preferred language onscreen to enter the main UI. Hold the Power/Lock button while the M155 is on and a shutdown dialog will pop up. You can select to turn off or reboot the player.

6

English Portable High Resolution Music Player

Charging

The M155 supports fast charging. To achieve the designed charging time, it is recommended to use a USB power source of QC 3.0 or one that supports PD protocol.

Gestures

- 1) Return to previous menu: swipe right from the left edge of the screen, or swipe left from the right edge.
- 2) Return to home menu: swipe up from the bottom edge of the screen
- 3) Multitask managing: swipe up from the bottom edge of the screen and then hold

Working modes switch

The M155 has five working modes: Android mode, Pure Music mode, USB DAC mode, Bluetooth Receiving mode and AirPlay mode. The M155 will default to enter Android mode when it powers on for the first time. You can switch to other working modes on the drop-down or Settings menu.

- 1) **Android mode/Pure Music mode**
You would need to install the MTP driver before connecting the M155 to the computer for data transfer. Please download the MTP driver on our website and follow relevant instructions to install it.
- 2) **USB DAC mode:**
When switching to the USB DAC mode for the first time, please download the USB DAC driver on our website and follow relevant instructions to install it.
- 3) **Bluetooth Receiving mode:**
When switching to the Bluetooth Receiving mode for the first time, the M155 will automatically enter the pairing state. The next time it enters Bluetooth Receiving mode, it will reconnect to the last connected device automatically.
-Force the device to enter pairing mode: Hold the Play/Pause button for about 3 seconds.
-Manually enter reconnecting mode: Short press the Play/Pause button when in pairing mode.
-Clear current pairing: Hold the Previous and Next track buttons at the same time for about 3 seconds.
-Play/Pause: Short press the Play/Pause button.
-Previous/Next track: Short press the Previous/Next track button.
- 4) **AirPlay mode**
When working in AirPlay mode, the M155 requires a valid WiFi connection. Please confirm that it is connected to an available network before entering the AirPlay mode.
Note: The MTP driver for the MAC system and the USB DAC driver for the Windows system can be found in the FiO Driver disk when connecting the M155 to a computer. Or, you can download the corresponding driver at http://www.fio.com/Driver_Download.

7

English Portable High Resolution Music Player

HOLD switch

When the HOLD switch is turned on, all buttons on the side of the M155 will be locked to prevent unintended touches as default (You can choose the button that will still be available on the settings menu beforehand). When the HOLD switch is turned off, all buttons will be available.

Enhanced over-ear headphone mode

When a fast-charging power adapter is inserted in the M155 and is detected, an "Enhanced over-ear headphone mode" will show up on the GAIN settings menu. Meanwhile, a dialogue prompt of "Switch to Enhanced over-ear headphone mode?" will pop up, and you can decide whether to switch it based on your needs.

Firmware upgrade

- 1) **Over-the-air (OTA) automatic upgrade**
Turn on the WiFi function on the M155 and connect it to an available network. It will automatically detect if there is a new firmware. If no firmware is detected, please tap "Technical Support -> Firmware Update -> Online Upgrade" to check and upgrade the firmware manually.
- 2) **Upgrade through a microSD card**
Please download the firmware on our website and follow relevant instructions to upgrade it.
Download link: http://www.fio.com/supports

Notes and Precautions

- ★ Please do not repair or disassemble the product on your own and do not put it in water.
- ★ Please charge the battery on a regular basis to secure the battery life if this product has not been used for a long time.
- ★ Please do not use the battery after it was soaked in water; do not use the battery if it is severely swollen; do not disassemble, bump and squeeze the battery, or drop it into fire.
- ★ It is recommended to use a suitable charger in case of a high-voltage adaptor causing damage to the device.
- ★ In the likely event that the M155 hangs up, you may hold the Power/Lock button for over 10 seconds to force a reboot.

Accessories

(please check if the following items are included)

- M155
- Leather case
- USB cable
- Quick start guide
- Warranty card
- Ejector pin

8

English Portable High Resolution Music Player

To Learn More

- For related video instructions of the M155 and FAQ (Frequently Asked Questions), please scan the QR code below.
- To learn more about the product, please visit our website: www.fio.com.
- To check the CMIIT-ID of the M155, please go to the menu of Settings->System->Legal information.

Due to continuous improvement, every specification and design is subject to change at any time without further notice.

WEEE Directive & Product Disposal

At the end of its serviceable life, this product should not be handed as household or general waste. It should be handed over to the applicable collection point for the recycling of electrical and electronic equipment, or returned to the supplier for disposal.

Internal/Supplied Batteries:
This symbol on the battery indicates that the battery is to be collected separately. This battery is designed for separate collection at an appropriate collection point.
Qualcomm is a trademark of Qualcomm Incorporated, registered in the United States and other countries. aptX is a trademark of Qualcomm Technologies International Ltd., registered in the United States and other countries.

Hereby, Guangzhou FiiO Electronics Technology Co., Ltd declares that this device is in compliance with Directive 2014/53/EU. The full text of the EU declaration of conformity is available at: www.fio.com/doc

Function	Frequency	Maximum output power
Bluetooth	2402-2480MHz	12.47dBm
	2412-2472MHz	12.47dBm
	5180-5320MHz	12.47dBm
WiFi	5500-5825MHz	12.47dBm

For this radio device, the following restrictions on putting into service or of requirements for authorisation of use apply in BE, BG, CZ, DK, DE, EE, IE, EL, ES, FR, HR, IT, CY, LV, LT, LU, HU, MT, NL, AT, PL, PT, RO, SI, SK, FI, SE, UK, IS, LI, NO, CH, TR: 5150-5350 MHz band is restricted to indoor operations only.

9

English Portable High Resolution Music Player

FCC NOTICE:

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

The equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. The equipment should be installed and operated with minimum distance 20 cm between the radiator & your body.

Master Quality Authenticated

The M155 includes MQA technology, which enables you to play back MQA audio files and streams, delivering the sound of the original master recording. The M155 Now Playing screen shows green or blue dot next to MQA logo to indicate that the unit is decoding and playing an MQA stream or file, and denotes provenance to ensure that the sound is identical to that of the source material. It shows blue dot to indicate it is playing an MQA Studio file, which has either been approved in the studio by the artist/producer or has been verified by the copyright owner.

10